PolaRx5 **Multi-frequency GNSS Reference Receiver**





Key Features

- Tracks all visible GNSS signals (GPS, GLONASS, Galileo, BeiDou, IRNSS)
- High precision, low noise measurements
- Unique interference monitoring
- Powerful web interface and logging tools
- Rugged housing and multiple interfaces
- Up to 8 independent logging sessions
- Logging both internally and to an external device

PolaRx5 is a versatile and robust multi-frequency GNSS reference receiver. The unique design of its tracking provides measurements with the lowest noise on the market while constantly monitoring and protecting against ionospheric interference, multipath and other environmental effects.

Tracking of all visible signals

PolaRx5 features simultaneous high-quality tracking of all visible signals (L1, L2, L5, E5ab/AltBOC B3/E6 GPS/ GLONASS/Galileo/Beidou/IRNSS, SBAS) at low noise levels.

independent competitive tests.

GNSS+™ technology

The A Posteriori Multipath Estimator, unique in its ability to tackle short-delay multipath, enhances the measurement quality while LOCK+ tracking guarantees robust tracking of rapid signal dynamics during scintillation events or earthquakes. Advanced interference analysis and adaptive mitigation using proprietary filtering facilitates use in difficult radio environments around airports or in the neighbourhood of chirp jammers.

Networking, remote operation, and data logging

Communication and (remote) management of the PolaRx5 is made easy with a powerful built-in web interface, which features secured access to all receiver settings and status information, data storage, and fast and robust firmware upgrading. SBF and RINEX data logging is possible on both a built-in 16GB memory and on an externally connected device. Up to 8 separate logging sessions can be defined. Logged data can be accessed through the built-in FTP server or automatically pushed to a FTP server.

Any device, any platform

Use any device with a web browser to operate the PolaRx5 via the built-in web server accessible over WIFI, Ethernet or USB.

PolaRx5 comes with RxTools, a suite of applications that complements the web interface with advanced display and analysis tools. RxTools is available for Windows and Linux.

PolaRx5

FEATURES

GNSS Technology

544 hardware channels for simultaneous tracking of all visible satellite signals

Supported signals: GPS (L1, L2, L5), GLONASS (L1,L2,L3) GALILEO (E1, E5ab, AltBoc, E6), BEIDOU (B1, B2, B3), IRNSS (L5), QZSS (L1, L2, L5) (Galileo, BeiDou and IRNSS are optional features)

All-in-view SBAS (EGNOS, WAAS, GAGAN, MSAS, SDCM) (incl. L5 tracking)

Up to 100Hz Raw data output (code, carrier, navigation data) (optional feature)

A Posteriori Multipath Estimator (APME+) including code and phase multipath mitigation

AIM+/WIMU interference mitigation unit, including chirp

Scalable Power Consumption

All multipath mitigation and smoothing algorithms can be disabled

Spectrum analyzer

RTK & DGNSS Base (optional feature)

Formats

RTCM v2.2, 2.3, 3.0 or 3.1 (All MSM messages supported) CMR 2.0

Highly compact and detailed Septentrio Binary Format (SBF) output

NMEA v2.30 and v4.10 output format

Includes intuitive GUI (RxControl, web interface and RxTools) and detailed operating and installation manual

Support for standard MET/Tilt sensors

Connectivity

x PPS output (max 100Hz)

10 MHz reference input

4 hi-speed serial ports

1 Ethernet port (100MBps)

Integrated Wi-Fi (802.11 b/g/n)

Power-Over-Ethernet

1 full speed USB port

1 USB host for external disk

16 GB standard on-board logging

Up to 8 simultaneous logging sessions

Advanced web interface providing all receiver controls, status monitoring, ftp server, ftp push

Ntrip server and client

Convenient TCP/IP socket interface for easy integration with your software applications

PERFORMANCE

E5 AltBOC

Measurement precision^{1,2,3}

C/A pseudoranges 5 cm (GPS)4 0.16 m (GPS)5,6 7 cm (GLO)4 0.25 m (GLO)^{5,7} 8 cm (GALILEO)5,6 E1 pseudoranges L5/E5ab 6 cm (GALILEO)5,6

E6 pseudoranges 7 cm (GALILEO)5,6 GPS P2 pseudoranges⁵ 0.1 m $0.1 \, \mathrm{m}$

1.5 cm (GALILEO)5,6

1 mm

0.1 Hz

GLONASS P pseudoranges⁵ 8 cm (BEIDOU)5,6 B1/B2 pseudoranges 6 cm (BEIDOU)5,6 B3 pseudoranges

IRNSS L5 pseudoranges 16 cm L1 carrier phase 1 mm

L5/E5 carrier phase 13 mm E6/B3 carrier phase 1 mm L1/L2/L5 doppler 0.1 Hz B1/B2 doppler 0.1 Hz

E6/B3 carrier phase

L2 carrier phase

Update rate Measurements 100 Hz Position 1 Hz

Time accuracy²

1PPS 10 ns Event 20 ns

Time to first fix

Cold start8 $< 45 \, s$ Warm start9 < 20 s Re-acquisition avg 1.2 s

Tracking performance (C/N0 threshold)^{10,11,12}

Tracking 20 dB-Hz 33 dB-Hz Acquisition

PHYSICAL AND ENVIRONMENTAL

Size 235 x 140 x 37 mm Weight 880 g **Input voltage** 9 - 30 VDC

Antenna LNA Power Output

Output voltage +5 VDC Maximum current 200 mA

Power Consumption 1.7 - 5 W

Operating temperature -40 °C to +65 °C Storage temperature -40 °C to +85 °C **Humidity** 5 % to 95 % (non condensing)

Connectors

TNC female Antenna Ref in/out **BNC** female 1PPS out **BNC** female Power ODU 3 pins female COM1 ODU 7 pins female COM₂ ODU 7 pins female COM3/4/USB ODU 7 pins female **USB Host** ODU 5 pins female IN ODU 7 pins female OUT ODU 5 pins female ODU 4 pins female **Ethernet** WIFI-Antenna SMA female

- 1 1 Hz measurement rate
- 2 1 σ level
- 3 C/N0 = 45 dB-Hz
- ⁴ Smoothed
- 5 Non-smoothed
- ⁶ Multipath mitigation disabled
- Multipath mitigation enabled
- 8 No information available (no almanacs, no approximate position)
- ⁹ Ephemeris and approximate position known
- 11 Max speed 600 m/s
- ¹² Depends on user settings of tracking loop parameters



Europe

Greenhill Campus Interleuvenlaan 15G 3001 Leuven, Belgium

+32 16 30 08 00

Americas

Suite 200. 23848 Hawthorne Blvd Torrance, CA 90505, USA

+1 310 541-8139

Asia-Pacific

Level 901, The Lee Gardens 33 Hysan Avenue Causeway Bay, Hong Kong

+852 3959 8680





